

TECHNICAL SPECS - LIGHT

Note	The Muzenzaal is equipped with a fixed lighting plot.
Lights network	Subnet mask: 255.0.0.0 ELC dmxLAN node 8 Muzenzaal-lights: Basement. ELC dmxLAN node 3 Muzenzaal-lights stage Right. ELC dmxLAN node 3 Muzenzaal-lights.
FOH	To stage left 1x ethercom RJ45 cat 6a To stage right 1x ethercom RJ45 cat 6a ELC dmxLAN node 3. Input 1: sACN 1 Hall fixtures Input 2: Free port Input 3: Free port
Flybars	ELC dmxLAN Node 8 Muzenzaal-lights: House lights = sACN 1 Flybar 1 = sACN 4 Flybar 2 = sACN 3 Flybar 3 = sACN 2 Robe lparfects around the stage = sACN 5 Front lights flybar = sACN 6 Front lights side flybars = sACN 8
Stage Left	ELC dmxLAN node 3 Stage left sACN 7 = iparfects on stages sACN 8 = free port in or output sACN 9 = free port in or output
Dimming	We can provide on stage a 24 channel SRS dimming pack. No dimmers on flybars.
Desk	1x Avolite Tiger touch 2 + wing Console IP: 2.0.0.151
Titan version	16
Fixed orchestra fixtures	Above the stage are 28 ETC Selador desire D40 Studio HD, used as fixed orchestra top light.
Front fixtures	10 x JB-Lighting P12 HC
Other fixtures	Manteau lights left and right Each side 2x ADB Fresnel 1 Kw
Fixed light fixtures on stage	6x JB Lighting P9 spot beams 4x Robe Spider 12x Robe Ledbeam 150 9x Robe lparfects 150 rgbw 20x robe lparfect 150 rgba 28x ETC desire D40 Studio HD
Floor lights	6x Robe lparfects 150 rgbw
Horizon lights	14x Robert Juliat LEDhorizon Dalis 860
Guest console IP	2.0.0.152
Smoke	Swefog Ultimate 3000

Flybar 3	Mode	Adress	sACN
Robe Spiider	3	1	2
Robe Spiider	3	34	2
Robe Spiider	3	67	2
Robe Spiider	3	100	2
JB Lighting P9 Beamspot	2	133	2
JB Lighting P9 Beamspot	2	172	2
JB Lighting P9 Beamspot	2	211	2
JB Lighting P9 Beamspot	2	250	2
Robe Ledbeam	1	289	2
Robe Ledbeam	1	311	2
Robe Ledbeam	1	333	2
Robe Ledbeam	1	355	2
Robe iParfect 150 RGBA	1	377	2
Robe iParfect 150 RGBA	1	394	2
Robe iParfect 150 RGBA	1	411	2
Flybar 2	Mode	Adress	sACN
Robe Ledbeam 150	1	1	3
Robe Ledbeam 150	1	23	3
Robe Ledbeam 150	1	45	3
Robe Ledbeam 150	1	67	3
Robe iParfect 150 RGBA	1	89	3
Robe iParfect 150 RGBA	1	106	3
Robe iParfect 150 RGBA	1	123	3
Flybar 1	Mode	Adress	sACN
Robe Ledbeam 150	1	1	4
Robe Ledbeam 150	1	23	4
Robe Ledbeam 150	1	45	4
Robe Ledbeam 150	1	67	4
Robe iParfect 150 RGBA	1	89	4
Robe iParfect 150 RGBA	1	106	4
Robe iParfect 150 RGBA	1	123	4
JB Lighting P9 Beamspot	2	140	4
JB Lighting P9 Beamspot	2	179	4
Front fixtures left & Right	Mode	Adress	sACN
JB Lighting P12 HC	2	1	8
JB Lighting P12 HC	2	64	8
JB Lighting P12 HC	2	127	8
JB Lighting P12 HC	2	190	8
Front lights	Mode	Adress	sACN
Jb Lighting P12 HC	2	1	6
Jb Lighting P12 HC	2	64	6
Jb Lighting P12 HC	2	127	6
Jb Lighting P12 HC	2	190	6
Jb Lighting P12 HC	2	253	6
Jb Lighting P12 HC	2	316	6

Extra orchest lights	Mode	Adress	sACN
Robe iParfect 150 FW	1	1	5
Robe iParfect 150 FW	1	18	5
Robe iParfect 150 FW	1	35	5
Robe iParfect 150 FW	1	52	5
Robe iParfect 150 FW	1	86	5
Robe iParfect 150 FW	1	103	5
Robe iParfect 150 FW	1	120	5
Robe iParfect 150 FW	1	137	5
Robe iParfect 150 FW	1	154	5
Robe iParfect 150 FW	1	171	5
Robe iParfect 150 FW	1	188	5
Robe iParfect 150 FW	1	205	5
Robe iParfect 150 FW	1	222	5
Robe iParfect 150 FW	1	239	5
Robe iParfect 150 FW	1	256	5
Robe iParfect 150 FW	1	273	5
Robe iParfect 150 FW	1	290	5
Robe iParfect 150 FW	1	307	5
Robe iParfect 150 FW	1	324	5
Orchest main top Lights	Mode	Adress	sACN
ETC d40 studio hd	Direct	65	1
ETC d40 studio hd	Direct	74	1
ETC d40 studio hd	Direct	83	1
ETC d40 studio hd	Direct	92	1
ETC d40 studio hd	Direct	101	1
ETC d40 studio hd	Direct	110	1
ETC d40 studio hd	Direct	119	1
ETC d40 studio hd	Direct	128	1
ETC d40 studio hd	Direct	137	1
ETC d40 studio hd	Direct	146	1
ETC d40 studio hd	Direct	155	1
ETC d40 studio hd	Direct	164	1
ETC d40 studio hd	Direct	173	1
ETC d40 studio hd	Direct	182	1
ETC d40 studio hd	Direct	191	1
ETC d40 studio hd	Direct	200	1
ETC d40 studio hd	Direct	209	1
ETC d40 studio hd	Direct	218	1
ETC d40 studio hd	Direct	227	1
ETC d40 studio hd	Direct	236	1
ETC d40 studio hd	Direct	245	1
ETC d40 studio hd	Direct	254	1
ETC d40 studio hd	Direct	263	1
ETC d40 studio hd	Direct	272	1
ETC d40 studio hd	Direct	281	1

House lights	Mode	Adress	sACN
Robe iparfect 150 FW		1	7
Robe iparfect 150 FW		18	7
Robe iparfect 150 FW		35	7
Robe iparfect 150 FW		52	7
Robe iparfect 150 FW		69	7
Robe iparfect 150 FW		86	7
Manteau left / right	Mode	Adress	sACN
ADB fresnel		7 8 9 10	1

ETC d40 studio hd	Direct	290	1
ETC d40 studio hd	Direct	299	1
ETC d40 studio hd	Direct	308	1
House Lights	Mode	Adress	sACN
House lights balcony		1	1
Chandelier main hall		2	1
Chandelier main hall		3	1
House lights hall right		4	1
House lights hall Left		5	1

DOWNLOADS

FULL LIGHT SET-UP FOR CONCERT >

FULL LIGHT SET-UP FOR THEATRE >